

PARTS LIST

NUTONE MODELS S-152 AND S-153 INTRUDER/FIRE SYSTEMS

REFERENCE NUMBER	NUTONE PART NUMBER	DESCRIPTION
TRANSISTORS		
TR-1	36590 (Motorola MPS A13)	Transistor
TR-2	36590 (Motorola MPS A13)	Transistor
TR-3	36590 (Motorola MPS A13)	Transistor
TR-4	36580 (Motorola M 6)	Transistor
TR-5	36580 (Motorola M 6)	Transistor
TR-6	36590 (Motorola MPS A13)	Transistor
TR-7	36590 (Motorola MPS A13)	Transistor
TR-8	36606 (Motorola MO 52)	Transistor
DIODES		
SCR-1	36507 (2N5060)	Selenium Controlled Rectifier
D-1	36549 (Motorola 1N4002)	
D-2	36549 (Motorola 1N4002)	
D-3	36549 (Motorola 1N4002)	
D-4	36549 (Motorola 1N4002)	
D-5	36661 (Motorola 1N5258)	Zener
RESISTORS		
R-1		10 Ohms
R-2		68 Ohms 2 Watt
R-3		120 Ohms 2 Watt
* R-4		10 Ohms
R-5		2.2K Ohms
R-6		560K Ohms
R-7		180K Ohms
R-8		10K Ohms
R-9		1 Meg Ohm
R-10		1K Ohm
R-11		1K Ohm
R-12		120 Ohms
R-13		680 Ohms
R-14		2.2K Ohms
* R-15		33K Ohms
* R-16	34042 Potentiometer	500K Ohms
R-17		2.2K Ohms
R-18		22 Ohms
R-19		5.6K Ohms
R-20		100K Ohms

PARTS LIST (continued)

REFERENCE NUMBER	NUTONE PART NUMBER	DESCRIPTION
RESISTORS (continued)		
R-21		10K Ohms
R-22		180K Ohms
R-23		10K Ohms
R-24		56K Ohms
R-25		47K Ohms
R-26		10K Ohms
R-27		100 Ohms
R-28		680 Ohms
R-29		100K Ohms
R-30		2.2K Ohms
* Used on S-152 only		
CAPACITORS		
C-1	35068-113	50mfd @ 50V DC
C-2	35075	2500mfd @ 15V DC
C-3	35076-101	.22mfd @ 12V DC
C-4	35076-101	.22mfd @ 12V DC
C-5	35076-101	.22mfd @ 12V DC
* C-6	35068-102	300mfd @ 15V DC
* C-7	35068-102	300mfd @ 15V DC
C-8	35068-108	10mfd @ 6V DC
C-9	35068-108	10mfd @ 6V DC
* C-10	35076-101	.22mfd @ 12V DC
* C-11	35068-118	8mfd @ 25V DC
C-12	35076-101	.22mfd @ 12V DC
* Used on S-152 only		
RELAYS		
RY-1	39180	Latching Relay
SWITCHES		
SW-1	34601	SPST Fire Test
* SW-2	34602	DPDT Home-Exit
SW-3	34603	DPDT Reset
SW-4	34604	DP3T Off-Test-On
PILOT LAMPS		
PL-1	0475	Bulb
PL-2	0475	Bulb
TRANSFORMER		
T-1	9964	NuTone 301N Power
PRINTED CIRCUIT BOARDS		
PCB-1	41230	P/C Board Model S-152
PCB-2	41231	P/C Board Model S-153