

PARTS LIST

Ref. No.	Part No.	Description	Ref. No.	Part No.	Description
TUBES			COMPONENT COMBINATIONS		
V1		12BE6, Converter	K1	B-37502	Audio Couplate—220 mmf, (2) 5000 mmf, (2) 250 mmf, (2) 470K Ω , 6.8 meg.
V2		12BA6, IF Amplifier			
V3		12AX7, AF Amp., Intercom Preamp.			
V4		50C5, Output			
V5		35W4, Rectifier			
CAPACITORS			T1	B-30513	INPUT TRANSFORMERS
C1		220 mmf @ 1000V, GMV, Ceramic Disc	T2	B-30512	Output Transformer
C2		10 mmf @ 1000V, $\pm 10\%$, NPO, Ceramic Disc	L1	B-30024	COILS
C3		10 mmf @ 1000V, $\pm 10\%$, NPO, Ceramic Disc	L2	B-30025	Antenna
C4		330 mmf @ 1400V, GMV, Ceramic Disc	L3	C-30511	Oscillator Coil
C5		33 mmf @ 1000V, $\pm 10\%$, N2200, Ceramic Disc	L4	C-30511	Input IF
C6		10,000 mmf @ 1000V, GMV, Ceramic Disc			Output IF
C7		220 mmf @ 1000V, GMV, Ceramic Disc	SP1	B-36025	SPEAKERS
C8		.047 mfd @ 600V, $\pm 20\%$, Tubular	SP2	B-36003	5" (3.2 Ω), Master Station
C9		10,000 mmf @ 1000V, GMV, Ceramic Disc	SP3	B-36030	3½" (3.2 Ω), Model 2006
C11A	B-35021	40 mfd @ 150V, Electrolytic	SP4	C-36008	4" (3.2 Ω), Model 2025
B		40 mfd @ 150V, Electrolytic			5" (3.2 Ω), Model 2026
C		80 mfd @ 150V, Electrolytic			8" (3.2 Ω), Model 2020
C12		1000 mmf @ 1000V, GMV, Ceramic Disc	MISCELLANEOUS		
C13		.047 mfd @ 600V, $\pm 20\%$, Tubular	M1	C-35022	Tuning Gang, 2 Section
C14		10,000 mmf @ 1000V, GMV, Ceramic Disc	M2	A-31023	Phono/Intercom—Radio/Intercom Switch; DPDT Slide Type
C15		220 mmf @ 1000V, GMV, Ceramic Disc	M3	A-34515	Master Station Talk-Listen Switch; DPDT Slide Type, Spring Return
C16		.047 mfd @ 600V, $\pm 20\%$, Tubular	M4	A-34503	Master Speaker Switch; Single Pole, 3-Position, Slide Type
C17		.047 mfd @ 600V, $\pm 20\%$, Tubular	M5	A-34503	Remote Station Selector Switch #1; Single Pole, 3-Position, Slide Type
C18		5000 mmf, 1000V, GMV, Ceramic Disc	M6	A-34503	Remote Station Selector Switch #2; Single Pole, 3-Position, Slide Type
RESISTORS			M7	A-34503	Remote Station Selector Switch #3; Single Pole, 3-Position, Slide Type
R1		1 meg, ½ Watt, $\pm 10\%$, Carbon	M8	A-34503	Remote Station Selector Switch #4; Single Pole, 3-Position, Slide Type
R2		22K Ω , ½ Watt, $\pm 10\%$, Carbon	M9	A-34503	Remote Station Selector Switch #5; Single Pole, 3-Position, Slide Type
R3		1000 Ω , ½ Watt, $\pm 10\%$, Carbon	M10	A-34503	Remote Station Selector Switch #6; Single Pole, 3-Position, Slide Type
R4		120 Ω , ½ Watt, $\pm 10\%$, Carbon	M11	A-34503	Remote Station Selector Switch #7; Single Pole, 3-Position, Slide Type
R5		2.2 meg, ½ Watt, $\pm 10\%$, Carbon	M12	A-34503	Remote Station Selector Switch #8; Single Pole, 3-Position, Slide Type
R6		330K Ω , ½ Watt, $\pm 10\%$, Carbon	M13	A-31105	Phono Jack
R7	B-34010	500K Ω , Carbon, Master Volume Control and Off-On Switch	M14	D-40018	Printed Circuit Terminal Board Assembly (Completely wired and soldered including selector switches M5 thru M12)
R8		3.3 meg, ½ Watt, $\pm 10\%$, Carbon	M15	A-34500	Remote Speaker Talk-Listen Switch (Used in Speaker Models 2006, 2025 and 2026); SPDT Slide Type, Spring Return
R9		180 Ω , 1 Watt, $\pm 10\%$, Carbon	M16	A-34511	Remote Speaker Talk-Listen Switch (Used in Speaker Model 2020); SPDT Rotary, Wafer Type, Spring Return
R10		220K Ω , ½ Watt, $\pm 10\%$, Carbon	M17	A-31026	Recessed Plug
R11		5600 Ω , ½ Watt, $\pm 10\%$, Carbon		A-36508	Detector, 1N295
R12		220 Ω , 2 Watt, $\pm 10\%$, Carbon		40050	Printed Circuit Board Assembly (Completely wired and soldered including all Board Mounted components)
R13		3.3 Ω , ½ Watt, $\pm 10\%$, Carbon			
R14		10K Ω , ½ Watt, $\pm 10\%$, Carbon			
R15		6.8 meg, ½ Watt, $\pm 10\%$, Carbon			
R16		10 Ω , 1 Watt, $\pm 10\%$, Carbon			
R17		22 Ω , ½ Watt, $\pm 10\%$, Carbon			
R18		1 meg, ½ Watt, $\pm 10\%$, Carbon			
R19		820K Ω , ½ Watt, $\pm 10\%$, Carbon (Used in Canadian Models only)			
R22		22 Ω , ½ Watt, $\pm 10\%$, Carbon			
R23	B-34000	20 Ω , Wirewound, Remote Speaker Volume Control			

PARTS LIST—(cont'd)

<i>Ref. No.</i>	<i>Part No.</i>	<i>Description</i>	<i>Ref. No.</i>	<i>Part No.</i>	<i>Description</i>
MISCELLANEOUS—(cont'd)			MISCELLANEOUS—(cont'd)		
D-40010-89		Front Panel Assembly. (Master Unit, Model 2031)	C-37018		Grille (Master Unit, Models 2053 and 2054)
D-4001-12		Front Panel Assembly. (Master Unit, Model 2032)	A-31119		Dial Pointer
D-40013-14		Front Panel Assembly. (Master Unit, Model 2053)	A-31126		Knob, Tuning (Master Unit, Models 2031 and 2054)
D-40013-22		Front Panel Assembly. (Master Unit, Model 2054)	A-31137		Knob, Volume (Master Unit, Models 2031 and 2054)
C-32041		Front Panel Inlay (Master Unit, Model 2053)	A-31125		Knob, Tuning (Master Unit, Model 2032 & 2053)
C-32042		Front Panel Inlay (Master Unit, Model 2054)	A-31136		Knob, Volume (Master Unit, Model 2032 & 2053)
			A-37023		Nameplate (Master Unit, Model 2031)
			A-37022		Nameplate (Master Unit, Model 2032)

NuTone Housing Products

[Redacted]
 Madison & Red Bank Roads, Cincinnati, Ohio 45227

Form No. 37079
 Printed in U.S.A. 5-77 - HI